

HAPTIC FEEDBACK SENSATIONS BASED ON AUDIO OUTPUT FROM COMPUTER DEVICES

BY INVENTOR

Stephen D. Rank

BACKGROUND OF THE INVENTION

The present invention relates generally to systems for allowing humans to interface with computer systems, and more particularly to methods for providing haptic feedback to the user interfacing with one or more computer applications involving sound output.

A user can interact with an environment displayed by a computer to perform functions and tasks on the computer, such as playing a game, experiencing a simulation or virtual reality environment, using a computer aided design system, operating a graphical user interface (GUI), navigate web pages, etc. Common human-computer interface devices used for such interaction include a mouse, joystick, trackball, gamepad, remote control, steering wheel, stylus, tablet, pressure-sensitive sphere, or the like, that is in communication with the computer system controlling the computer environment. The computer updates the environment in response to the user's manipulation of a physical manipulandum such as a joystick handle, button, or mouse, and provides visual and audio feedback to the user utilizing the display screen and audio speakers. The computer senses the user's manipulation of the user object through sensors provided on the interface device that send locative signals to the computer.

In some interface devices, kinesthetic force feedback and/or tactile feedback is also provided to the user, more generally known collectively herein as "haptic feedback." These types of interface devices can provide physical sensations which are felt by the user manipulating a user manipulandum of the interface device. One or more motors or other actuators are coupled to the manipulandum and are connected to the controlling computer system. The computer system controls forces on the manipulandum in conjunction and coordinated with computer events and interactions by sending control signals or commands to the actuators. The computer system can thus convey physical force sensations to the user in conjunction with other supplied feedback as the user is grasping or contacting the interface device or manipulatable object of the interface device.

The audio feedback provided to the user is an inherent part of many application programs, especially games. Some existing haptic feedback devices are designed to provide haptic

sensations based directly on the sound output from the computer. The sound output waveform is directly routed to the interface device so that tactile sensations, such as vibrations, are based directly on the sound output waveform or a filtered portion thereof, much like the way a speaker operates.

- 5 A disadvantage of existing haptic sensations based on direct sound waveforms is that the haptic sensations are simple effects based directly on the sound signals. No evaluation or processing of the sound signals is accomplished before sending the signals to the haptic device. This can cause undesirable or disconcerting haptic sensations to be output to the user since not all of the sound output is appropriate for directly translation into haptic sensations.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210

SUMMARY OF THE INVENTION

The present invention is directed toward triggering the output of haptic sensations based on sound output from a computer device. The output of haptic sensations is intelligently triggered by analyzing sound data for features, allowing an enhanced user experience.

More particularly, an interface device of the present invention provides a method for triggering haptic sensations from sound features detected in sound output from a computer, where the haptic sensations are able to be output to a user of a haptic feedback device in communication with the computer. A portion of sound data is stored that is output to a user as audio from an application program running on the computer. The sound data is stored in a memory buffer of the computer. The portion of sound data is analyzed using intelligent heuristics to extract at least one sound feature from the portion of sound data. The execution of at least one haptic effect is triggered based on the sound feature(s), where the haptic effect is commanded to the haptic feedback device approximately correlated to the output of the portion of sound to the user as audio. The haptic effect causes a haptic sensation to be output to the user.

The triggered haptic sensation is preferably assigned to the sound features found in the sound data. In some embodiments, analyzing the portion of sound data can include processing the sound data into multiple different frequency ranges and searching for sound features in each of the frequency ranges. A haptic effect can be triggered for each of the frequency ranges if the sound feature is present in that frequency range. Filters can be applied to the sound data, or a fast Fourier transform can be used. Each frequency range can be associated with or mapped to a different haptic sensation. For example, each of the frequency ranges can be associated with a periodic haptic sensation having a different frequency. Other types of haptic sensations can also be mapped and assigned to sound features so that they will trigger upon output of those sound features.

The present invention advantageously allows haptic feedback to be output by a computer system running an application program having sound output. The present invention intelligently assigns haptic sensations to features in the sound data to provide haptic feedback relevant to events in the application program which caused the sound output. This results in an overall improvement in user experience of the haptic feedback based on sound output.

These and other advantages of the present invention will become apparent to those skilled in the art upon a reading of the following specification of the invention and a study of the several figures of the drawing.

BRIEF DESCRIPTION OF THE DRAWINGS

FIGURE 1 is a block diagram illustrating one embodiment of a haptic feedback system
5 suitable for use with the present invention;

FIGURE 2 is a side cross-sectional view of a mouse embodiment of the haptic feedback
device suitable for use with the present invention;

FIGURE 3 is a flow diagram illustrating a first embodiment of a method of the present
invention for providing haptic effects to be output as haptic sensations based on provided sound
data;

FIGURE 4 is a flow diagram illustrating one embodiment for the step of Fig. 3 in which
the sound data stored in the buffer is processed and analyzed; and

FIGURE 5 is a flow diagram illustrating another embodiment for the step of Fig. 3 in
which the sound data stored in the buffer is processed and analyzed.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

FIGURE 1 is a block diagram illustrating a computer system 10 suitable for use with the present invention, including a haptic feedback interface device 12 in communication with a host computer 14.

Host computer 14 preferably includes a host microprocessor 20, a clock 22, a display screen 26, and an audio output device 24. The host computer also includes other well known components, such as random access memory (RAM), read-only memory (ROM), and input/output (I/O) electronics (not shown). The host computer 14 is a computing device that can take a wide variety of forms. For example, in the described embodiments computer 14 is a personal computer or workstation, such as a PC compatible computer or Macintosh personal computer, or a Sun or Silicon Graphics workstation. Such a computer 14 can operate under the Windows™, MacOS™, Unix, MS-DOS, or other operating system. Alternatively, host computer 14 can be one of a variety of home video game console systems commonly connected to a television set or other display, such as systems available from Nintendo, Sega, Sony, or Microsoft. In other embodiments, host computer 14 can be a "set top box", a "network-" or "internet-computer", a portable computer or game device, personal digital assistant (PDA), etc.

Host computer 14 preferably implements a host application program with which a user is interacting via device 12 and other peripherals, if appropriate. In the context of the present invention, the host application program is a digital audio editing program, as described in greater detail below. Other application programs that utilize input of device 12 and output haptic feedback commands to the device 12 can also be used. The host application program preferably utilizes a graphical user interface (GUI) to present options to a user and receive input from the user. This application program may include the haptic feedback functionality described below; or, the haptic feedback control can be implemented in another program running on the host computer, such as a driver or other application program. Herein, computer 14 may be referred as providing a "graphical environment," which can be a graphical user interface, game, simulation, or other visual environment. The computer displays "graphical objects" or "computer objects," which are not physical objects, but are logical software unit collections of data and/or procedures that may be displayed as images by computer 14 on display screen 26, as is well known to those skilled in the art. Suitable software drivers which interface software with haptic feedback devices are available from Immersion Corporation of San Jose, California.

Display device 26 can be included in host computer system 14 and can be a standard display screen (LCD, CRT, flat panel, etc.), 3-D goggles, projection device, or any other visual

output device. Display device 26 displays images as commanded by an operating system application, simulation, game, etc.

Audio output device 24, such as speakers, provides sound output to user. In the context of the present invention, other audio-related devices may also be coupled to the host computer, such as stereo receivers, amplifiers, etc. Other types of peripherals can also be coupled to host processor 20, such as storage devices (hard disk drive, CD ROM drive, floppy disk drive, etc.), printers, and other input and output devices.

The haptic feedback interface device 12, such as a mouse, knob, gamepad, trackball, joystick, remote control unit, PDA screen, etc., is coupled to host computer 14 by a bi-directional bus 30. The bi-directional bus sends signals in either direction between host computer 14 and the interface device. Bus 30 can be a serial interface bus, such as an RS232 serial interface, RS-422, Universal Serial Bus (USB), MIDI, or other protocols well known to those skilled in the art; or a parallel bus or wireless link. Some interfaces can also provide power to the actuators of the device 12.

Device 12 can include a local processor 40. Local processor 40 can optionally be included within the housing of device 12 to allow efficient communication with other components of the mouse. Processor 40 can be provided with software instructions to wait for commands or requests from computer host 14, decode the command or request, and handle/control input and output signals according to the command or request. In addition, processor 40 can operate independently of host computer 14 by reading sensor signals and calculating appropriate forces or commands from those sensor signals, time signals, and stored or relayed instructions selected in accordance with a host command. Suitable microprocessors for use as local processor 40 include the MC68HC711E9 by Motorola, the PIC16C74 by Microchip, and the 82930AX by Intel Corp., for example, as well as more sophisticated force feedback processors such as the Immersion Touchsense Processor. Processor 40 can include one microprocessor chip, multiple processors and/or co-processor chips, and/or digital signal processor (DSP) capability.

Microprocessor 40 can receive signals from sensor(s) 42 and provide signals to actuator 44 in accordance with instructions provided by host computer 14 over bus 30. For example, in a local control embodiment, host computer 14 provides high level supervisory commands to processor 40 over bus 30, and processor 40 decodes the commands and manages low level force control loops to sensors and the actuator in accordance with the high level commands and independently of the host computer 14. This operation is described in greater detail in US Patents 5,739,811 and 5,734,373, both incorporated herein by reference. In the host control loop, force commands from the host computer instruct the processor to output a force or force

sensation having specified characteristics. The local processor 40 reports locative and other sensor data to the host computer which the host computer uses to update executed programs. In the local control loop, actuator signals are provided from the processor 40 to actuator 44 and sensor signals are provided from the sensor 42 and other input devices 48 to the processor 40.

5 The processor 40 can process inputted sensor signals to determine appropriate output actuator signals by following stored instructions. Herein, the term "haptic sensation" or "tactile sensation" refers to either a single force or a sequence of forces output by the actuator which provide a sensation to the user. The term "haptic effect" generally refers to the commands, parameters, and/or data sent to the device that define a haptic effect and which results in a haptic

10 sensation when the effect is output as forces to the user by the device.

In yet other embodiments, other simpler hardware can be provided locally to device 12 to provide functionality as processor 40. For example, a hardware state machine or ASIC incorporating fixed logic can be used to provide signals to the actuator 44 and receive sensor signals from sensors 42, and to output tactile signals according to a predefined sequence, algorithm, or process.

15

In a different, host-controlled embodiment, host computer 14 can provide low-level force commands over bus 30, which are directly transmitted to the actuator 44 via processor 40. Host computer 14 thus directly controls and processes all signals to and from the device 12. In the simple host control embodiment, the signal from the host to the device can command the actuator to output a force at a predefined frequency and magnitude, or can include a magnitude and/or a direction, or be a simple command that indicates a desired force value to apply over time.

20

Local memory 52, such as RAM and/or ROM, is preferably coupled to processor 40 in device 12 to store instructions for processor 40 and store temporary and other data. For example, force profiles can be stored in memory 52, such as a sequence of stored force values that can be output by the processor, or a look-up table of force values to be output based on the current position of the user object. In addition, a local clock 54 can be coupled to the processor 40 to provide timing data, similar to the system clock of host computer 14; the timing data might be required, for example, to compute forces output by actuator 44 (e.g., forces dependent on calculated velocities or other time dependent factors). In embodiments using the USB

25 communication interface, timing data for processor 40 can be alternatively retrieved from the USB signal.

30

Sensors 42 sense the position or motion of the device and/or one or more manipulandums or controls and provides signals to processor 40 (or host 14) including information representative of the position or motion. Sensors suitable for detecting manipulation include digital optical

35 encoders, optical sensor systems, linear optical encoders, potentiometers, optical sensors,

velocity sensors, acceleration sensors, strain gauge, or other types of sensors can also be used, and either relative or absolute sensors can be provided. Optional sensor interface 46 can be used to convert sensor signals to signals that can be interpreted by the processor 40 and/or host 14.

Actuator(s) 44 outputs haptic sensations by transmitting forces to the housing or one or more manipulandums of the device 12 in response to signals received from processor 40 and/or host computer 14. Actuator 44 can be any of many types of actuators, including active actuators such as DC motors, voice coils, pneumatic or hydraulic actuators, torquers, piezoelectric actuators, moving magnet actuators, etc., or passive actuators such as brakes.

Actuator interface 50 can be optionally connected between actuator 44 and processor 40 to convert signals from processor 40 into signals appropriate to drive actuator 44. Interface 50 can include power amplifiers, switches, digital to analog controllers (DACs), analog to digital controllers (ADCs), and other components, as is well known to those skilled in the art. Other input devices 48 are included in device 12 and send input signals to processor 40 or to host 14 when manipulated by the user. Such input devices can include buttons, scroll wheels, d-pads, dials, switches, or other controls or mechanisms.

Power supply 56 can optionally be included in device 12 coupled to actuator interface 50 and/or actuator 44 to provide electrical power to the actuator, or be provided as a separate component. Alternatively, power can be drawn from a power supply separate from device 12, or be received across the bus 30. Also, received power can be stored and regulated by device 12 and thus used when needed to drive actuator 44 or used in a supplementary fashion. Some embodiments can use a power storage device in the device to ensure that peak forces can be applied (as described in U.S. Patent No. 5,929,607, incorporated herein by reference). Alternatively, this technology can be employed in a wireless device, in which case battery power is used to drive the tactile actuators. A safety switch 58 can optionally be included to allow a user to deactivate actuator 44 for safety reasons.

Many types of interface or control devices may be used with the present invention described herein. For example, such interface devices can include a haptic feedback trackball, joystick handle, steering wheel, knob, handheld remote control device, gamepad controller for video games or computer games, stylus, grip, wheel, button, cellular phone, PDA, touchpad, or other manipulatable object, surface, or housing.

FIGURE 2 is a side cross-sectional view of a mouse embodiment 100 of device 12 for use with the present invention.

Mouse device 100 includes a housing 101, a sensing system 102, and an actuator 104. Housing 101 is shaped to fit the user's hand like a standard mouse while the user moves the mouse in the planar degrees of freedom and manipulates the buttons 106. Other housing shapes can be provided in many different embodiments.

5 Sensor 102 detects the position of the mouse in its planar degrees of freedom, e.g. along the X and Y axes. In the described embodiment, sensor 102 includes a standard mouse ball 110 for providing directional input to the computer system. Alternatively, an optical sensor or other type of sensor can be used.

10 Mouse device 100 includes one or more actuators 104 for imparting haptic feedback such as tactile sensations to the user of the mouse. Actuator 104 is coupled to the housing 101 to provide haptic feedback to the user. In one embodiment, the actuator is coupled to an inertial mass that is moved by the actuator. Inertial forces caused by the motion of the inertial mass are applied to the housing of the mouse with respect to the inertial mass, thereby conveying haptic feedback such as tactile sensations to the user who is contacting the housing. Some
15 embodiments allow the actuator to move itself as the inertial mass. Such embodiments are described in greater detail in U.S. Patent No. 6,211,861 and U.S. Application No. 09/585,741, both incorporated herein by reference. Other types of interface devices, such as gamepads, handheld remote controls, cellular phones, PDA's, etc., can include such an actuator for inertial tactile sensations.

20 Other types of interface devices and actuators can also be used with the present invention. For example, gamepads, mice, or other devices can include an eccentric rotating mass coupled to a rotating shaft of an actuator to provide inertial tactile sensations on the housing or manipulandum of the device. Other types of haptic devices can provide kinesthetic force feedback, such as joysticks, knobs, scroll wheels, gamepads, steering wheels, trackballs, mice,
25 etc., in which forces are output in the sensed degree(s) of freedom of a manipulandum. For example, embodiments of a kinesthetic mouse haptic device are disclosed in U.S. Patent Nos. 6,100,874 and 6,166,723, both incorporated herein by reference in their entireties.

Sound Output with Haptic Feedback

30 The present invention improves the user experience in the output of haptic sensations coordinated with the sound output of one or more application programs (or other programs) running on the host computer.

The preferred embodiment of the present invention provides haptic effects for output to a haptic feedback device based on sound signals or data output by a host computer and which are output as haptic sensations to the user. In some alternate embodiments, the haptic effects can be similarly provided based on features in sound signals or data input to a computer system, e.g. from a microphone or audio device. Temporal features and characteristics of sound are identified and mapped to or associated with preprogrammed haptic effects. The haptic sensations based on these haptic effects can be rendered immediately on haptic feedback device 12, or can be stored in memory to form a "haptic profile" of a given sound. The method of the present invention is not to simply route sound signals directly to a haptic device for output as haptic sensations, as is done in the prior art, but to associate a variety of high-level sound features with a variety of high-level haptic sensations, using the sound features to trigger the output of the appropriate haptic sensations.

An important advantage of the present invention is that compelling haptic sensations are provided for any program that outputs sounds for a variety of events in that application program, e.g. games, without a software application developer having to expend effort in programming the haptic effects in the program. Thus, any game program off the shelf can be easily made to work with haptic feedback devices regardless of whether the game includes code to control haptic devices or whether it was only developed for non-haptic-feedback devices, allowing the user a more compelling interactive and immersive experience with a wide variety of programs. Furthermore, the present invention can approximately distinguish between types of sound effects and associate different haptic sensations with different events, allowing a more rich experience for the user.

In one embodiment, a low-level driver program running on the host computer performs the methods of the present invention. In other embodiments, other levels of software running on the host (or on a microprocessor of the haptic feedback device) can perform some or all of the features or steps of the present invention (application program, API, etc.). Program instructions for implementing the present invention can be stored as hardware (e.g. logic components) or software stored on a computer readable medium, such as electrical memory, magnetic disk, optical disk, magnetic tape, etc.

FIGURE 3 is a flow diagram illustrating a first embodiment 200 of a method of the present invention for providing haptic effects to be output as haptic sensations based on given sound data or sound signal. The method starts at 202, and in optional step 204, haptic effects are commanded to the device and not yet output to the user. For example, the haptic device 12 can include local memory that allows the device to store data for a number of different haptic effects. The haptic effects resident in the device memory can be played when a host command is received or based on other conditions (a predetermined time period has passed, etc.). The data sent to the device can include parameters for the haptic effects; e.g., for a periodic vibration effects, the parameters can

include a frequency, duration, and magnitude. The effects can be loaded to the device in step 204 and in some embodiments can be commanded to play, e.g. at a magnitude of zero, in preparation to be commanded to higher magnitudes at a later step. Step 204 is most appropriate for those embodiments in which the same set of haptic sensations are always output to the user. In other
5 embodiments, haptic effects can be commanded at the time they are to be output to the user.

In next step 206, sound data is received from an application program or other software layer or program running on the host computer, or alternately, direction from an external audio device. The sound data is preferably digital data that can be in any standardized format, such as MIDI, digital sound samples in a wav file, an mp3 file, etc. The sound data is received in step 206 when it is also
10 to be routed to an audio output device such as speakers and output to the user as sound. Typically, the sound data is generated by the application program from a sound event occurring in the application, such as a sound effect in a game resulting from game actions or events, music in a game or other application program playing after a game starts or other event occurs, a beep in a graphical user interface interaction, the playing of music from a CD or DVD, or other sound event. In the described embodiment, the sound data received at this step to be analyzed is currently being output
15 by speakers to the user. Thus, by the time the sound data is processed and haptic sensations output as described below, the sound data has already been output to the user. However, since a small amount of sound data is stored, only a delay of milliseconds occurs between sound and haptic output, which the user cannot discern. In other embodiments in which the sound data output is known in advance, haptic sensations can be output simultaneously, or close to simultaneously, with the sound data that triggered them.
20

In step 208, a predetermined amount of the received sound data is stored in a temporary buffer in the memory of the host computer 14. In one embodiment, this is an amount of data reasonably small enough to allow quick processing and associating with haptic sensations, while
25 large enough to permit meaningful processing and analysis. In one embodiment, a portion of sound data equivalent to about 10 ms of play is stored, although different amounts can be stored in other embodiments. For example, the sound can be digitally recorded in a 10 ms segment using DirectSound or other sound capture API on the host computer.

In step 210, the stored sound data is processed and analyzed to identify particular sound
30 characteristics or features which have been designated as relevant in the determination of which haptic sensations are to be output, i.e. these sound features are to act as cues to trigger the output of haptic sensations. In broad terms, the present invention uses intelligent heuristics to extract sound features that are likely to have meaning in an application program and to associate such sound features with predetermined, preprogrammed haptic sensations that correspond appropriately with
35 the extracted sound features and the likely events these features represent. For example, likely

events in many current video game applications may be explosions from bombs, grenades, missiles, etc., the firing of a weapon such as a gun or rocket, the crash of a vehicle, the patter of footsteps, the sound of an object splashing into water, an alert sound for alerting the player to some game event, etc. These events may have particular sound features which can be recognized from the received sound data after appropriate analysis.

A variety of different ways can be employed to process the data; some embodiments are described below with respect to Figs. 4 and 5. These particular embodiments perform processing on the sound data to divide the waveform represented by the sound data into a number of different frequency ranges according to the present invention. Each frequency range of sound can then be analyzed separately for particular sound features. This frequency range division has the advantage that sounds often occur in different frequency ranges based on the event that triggered the sound; for example, an explosion in a game may have a low frequency sound while a gun shot may have a higher frequency sound. Types of events might therefore be approximately distinguished based on the frequency range in which the sound is located, allowing different haptic effects to be commanded and output as described below.

Once the sound data has been processed and analyzed, in next step 212, haptic commands are output to the haptic device to cause haptic sensations to be output to the user manipulating the device. The haptic commands are triggered based on the sound features, if any, found in the sound data in step 210. Intelligent heuristics can be used to assign different haptic sensations to different types of sounds based, for example, on the frequencies of the sounds or other characteristics of the sounds. The haptic commands can cause device-resident haptic effects to start playing or play at a commanded magnitude. In one embodiment, the haptic effects that are already resident in memory on the device from step 204 are modified with new parameters or data as appropriate to implement the desired haptic sensations. Alternatively, new haptic effects can be created and commanded to be output immediately by the device as haptic sensations. As explained above, the haptic sensations resulting from the commands may be output slightly after the associated sound features have been output as audio, but preferably soon enough so that the user cannot tell that there was a delay.

In one embodiment, the commanded haptic sensations can be set to a magnitude proportional to the sound data magnitude in the associated frequency range. For example, embodiments discussed with reference to Figs. 4 and 5, the sound data is filtered or organized into 5 different frequency ranges. Each of these frequency ranges can have a different haptic sensation associated with it. For example, using an available inertial tactile feedback mouse, a periodic haptic effect of different frequency is associated with each of the frequency ranges. Thus, for example, a periodic haptic effect having a haptic frequency of 62 Hz (e.g., at or near a first resonance frequency of the haptic device to cause high magnitude sensations) is associated with the first sound frequency range (e.g., 0

Hz to 150 Hz). The other periodic haptic effects can have haptic frequencies of 75 Hz, 90 Hz, 115 Hz, and 250 Hz, each corresponding to another sound frequency range in ascending order (other periodic frequencies can be used in other embodiments). The magnitudes of each of these periodic haptic effects can be set to a value proportional to the magnitude of the sound data in the associated frequency range. A running average of magnitude of ambient sound levels can be used as a minimum threshold for haptic effect generation, e.g. if the sound signal for a particular frequency range has a higher magnitude than the threshold, then a haptic effect associated with that frequency range can be commanded to be output or can be commanded to have a magnitude above a zero level.

The method presented above thus varies the magnitudes of five different haptic effects based on the corresponding varying magnitudes in different frequency ranges of the sound signal represented by the sound data. With some sounds that have components in all the frequency ranges, this may cause five different haptic effects to be output at once. However, since many sound features that are spread across several frequency ranges last for a short amount of time, the user perceives only a short vibration or series of pulses rather than a mush of different frequencies. Other more sustained sound effects may be concentrated in only one or two frequency ranges which will cause only one or two haptic effects to be output simultaneously (the haptic effects for the other frequency ranges will be set to zero magnitude). The user will thus feel a haptic sensations that roughly corresponds to the sound effect's frequency. This is also discussed with respect to Fig. 4.

Thus, the amplitude of a haptic sensation that is associated with a particular frequency range or band can correspond directly with the magnitude level of a sound signal in that frequency band, as explained above. In addition to this continuous haptic output, sudden spikes of amplitude in the sound signal can be mapped to additional jolts, pulses, or other short, strong haptic sensations which can be overlaid on the continuous vibration sensations.

In other embodiments, more sophisticated haptic sensations can be output based on the sound data processing and analysis of step 210 and based on intelligent heuristics. In many applications such as games, the type of sound may be able to be determined based which frequency ranges it is primarily located. This allows a more sophisticated mapping scheme, where completely different haptic sensations can be mapped to different sound frequency ranges. This is also discussed with respect to Fig. 5.

For example, it is often the case that weapon fire in a video game application is associated with a sudden burst of high frequency sound. Using this fact as an intelligent heuristic, in step 210 the sound output data from the game can be analyzed and a feature that indicates that a high frequency sound has been output identified. For example, a particular frequency range can be checked for a sudden burst or spike in amplitude of sound. In step 212, a haptic sensation associated with weapon fire can be intelligently commanded to be output based on the sound burst found in the

sound. In some embodiments, the haptic sensation can be modified on the fly while the sound and the haptic sensations are playing, where the magnitude and duration of the haptic sensation is continually adjusted based on the magnitude of the sound burst above a predetermined threshold, the duration of the burst, and/or the specific frequency content of the burst.

5 In some embodiments, a completely different haptic profile can be selected for a sound feature based on the specifics of the sound feature, where a pre-programmed mapping between sound characteristics and haptic effects is consulted (e.g., a look-up table or data table can be stored in memory). For example, a sound burst in a very different frequency range might trigger a completely different haptic sensation. A low frequency sound burst in a video game might be, for example, the
10 sound of a footsteps of a character. An appropriate haptic sensation can be mapped to that sound feature, such as a low-frequency vibration or undulating force.

Some games or other programs may output similar sound effects for similar events to allow approximate mapping as discussed above. Other games and programs, however, may have different events associated with similar-sounding sounds. Therefore, in one embodiment, a particular look-up
15 table or other mapping data can be associated with each individual game (or other application program). Using the table, the method of the present invention can identify on the table which game is playing and then find the appropriate mapping between sound characteristics of that game and haptic sensations that have been assigned by the table's author. This allows for tuning of the heuristics tailored for specific games, enabling more accurate mappings. This can be advantageous
20 to developers, who will not have to put haptic effects or mappings in their games themselves, but can rely on the manufacturers of the haptic devices to put out driver updates including haptic mappings for games currently available based on the sound output.

In alternate embodiments, the haptic effects that are associated with the found sound features are not immediately output as haptic sensations to the user, but are instead stored in memory to form
25 a "haptic profile" of a given sound. This can be used to assist in the design of haptic effects. For example, a sound file can be loaded and the user can select a control in a graphical user interface to cause the method of the present invention to generate a compound haptic effect that corresponds to the sound. The generated haptic effect (or haptic magnitudes, force values, etc.) can be then used in a program by commanding the generated compound haptic effect. Alternatively, the haptic profile
30 (generated effect) can become a new haptic effect primitive to allow developers to create new effects based on this primitive, e.g. periodic effects, textures, temporal profiles, etc. can be created.

For example, a game may have hundreds of sound effects. The method of the present invention can be instructed to load the game's sound files and create haptic effects from the sound data in a standardized format (such as .ifr files, used in protocols created by Immersion Corp. of San
35 Jose, California) in a few seconds. Thus, a developer need not create each haptic effect manually,

saving great amount of development time. A designer could also examine the generated haptic effects and edit them, if desired. This is advantageous to developers who wish to add code to their games to command haptic effects to haptic devices in the traditional way, but who do not wish to spend large amounts of time designing the appropriate haptic effects.

After the output of the haptic sensation, the method returns to step 206 to check if further sound data is received. If so, a next portion of sound data is processed as discussed above. If no further sound data is received, the process is complete at 242 (to be started again the next time sound data is output).

FIGURE 4 is a flow diagram illustrating one embodiment for step 210 of Fig. 3, in which the sound data stored in the buffer is processed and analyzed. The method starts at 270, and in step 272, the stored sound data is set through multiple filters to isolate different frequency ranges. For example, to divide the sound data into five frequency ranges as described in the example above, a low-pass filter, a high-pass filter, and three bandpass filters can be employed. As one example, the low-pass filter can filter out all data in the frequencies outside 0-170 Hz, the first bandpass filter can filter out all frequencies except 170-430 Hz, the second bandpass filter can filter out all frequencies except 430 Hz-2 kHz, the third bandpass filter can filter out all frequencies except 2 - 10 kHz, and the high-pass filter can filter out all frequencies lower than 10 kHz.

In step 274, a running average of the sound magnitude from each of the filter outputs is maintained. This allows ambient sounds output from the computer to be averaged out so that only sounds louder than the ambient level will trigger haptic sensations. In next step 276, the magnitudes of the filter outputs are scaled to a range that is required for the haptic device 12 that the user is using. Thus, the actual filter outputs are not used to generate haptic sensations as in the prior art, but new haptic commands and effects are created based on the filter outputs.

In some embodiments, the square of each filter's output magnitude can be scaled. This may be more effective in some embodiments to pick out only the larger peaks or spikes in each frequency range of sound data and reduce a sustained rumble/vibration of the device that may occur from too many peaks being detected.

In next step 278, periodic haptic effects are assigned to each of the filter's outputs. The periodic effects can each be assigned a magnitude equal to the scaled magnitude found for each filter. If a filter has no output, i.e. no sound of that frequency range is present in the sound data, or if a filter's output is not above a predetermined threshold amplitude, then the haptic effect assigned to that frequency range would be assigned a magnitude of zero. The periodic sensations can each have one of five haptic frequencies found to be effective in conveying the corresponding sound frequency. Such periodic haptic sensations, such as vibrations, are quite appropriate for tactile devices such as

gamepads or mice providing inertial tactile sensations. The vibrations can also be output by kinesthetic feedback devices. Other types haptic sensations can also be output by kinesthetic device embodiments, having magnitudes based on the scaled magnitudes determined above. The type of haptic sensations assigned can be different in different embodiments, such as pops, jolts, springs, damping, etc., can also be output having magnitudes based on the scaled magnitudes; for example, a pre-programmed mapping can be consulted to assign a mapped haptic effect.

The method is then complete at 280. The assigned periodic haptic sensations can be used in the next step 212 of Fig. 3, where haptic sensations are output to the user by commanding the haptic effects to the haptic feedback device.

FIGURE 5 is a flow diagram illustrating a different embodiment 210' of step 210 of Fig. 3, in which the sound data stored in the buffer is processed and analyzed. The method starts at 290, and in step 292, a Fast Fourier Transform (FFT) is performed on the sound data to filter the data into different frequency components of the data's frequency spectrum. The frequency components each span a frequency range based on the number of components output by the FFT and the entire frequency range covered. For example, if the FFT has 512 outputs, and the entire frequency range of the sound data is about 22 kHz, the each FFT output frequency component has a frequency range of $22 \text{ kHz} / 512 = \text{about } 43 \text{ Hz}$. These frequency components can then be grouped to sum to desired frequency ranges. For example, to achieve the five frequency ranges similar to the embodiment of Fig. 4, four components can be combined to cover the first frequency range of 0 - 170 Hz, 6 components cover the range 170-430 Hz, 37 components cover the range 430 Hz - 2 kHz, 185 components cover the range 2 kHz - 10 kHz, and 256 components cover the range 10 - 22 kHz. Other frequency ranges and components can be used in other embodiments.

In next step 294, the method checks whether any of the frequency ranges grouped in step 292 have predetermined characteristics. These characteristics are features in the sound data that are significant enough to trigger the output of haptic sensations. In one embodiment, an average amplitude is maintained for each frequency range, and a spike in the amplitude is looked for. If a spike in amplitude of 3-4 times the average amplitude is found, then that is deemed significant and a haptic effect should be assigned to or triggered by that feature.

If predetermined characteristics are found, then the process continues to step 296 to assign haptic effects to those frequency ranges having the predetermined characteristics, and the process is complete at 298 and the method returns to step 212 of Fig. 3. If in step 294 no frequency ranges are found to have the desired characteristics, then the process is complete at 298 and the method returns to step 212 of Fig. 3.

The haptic effects that are assigned to the frequency ranges having the desired characteristics can be any of several different types and/or have different parameters, and need not have a magnitude proportional to the amplitude of the corresponding sound data. For example, a jolt, pulse, or detent can be mapped to any extracted sound features (such as rise in amplitude). The magnitude of the jolt or detent can be based on the frequency range in which the amplitude spike was found, e.g. lower frequency ranges can be assigned higher magnitude haptic sensations (or vice-versa). Periodic sensations, directional sensations (for haptic devices able to output forces in particular directions in degrees of freedom of the device), spring sensations, damping sensations, etc. can be mapped to the different frequency ranges. In one embodiment, a haptic sensation can be increased in magnitude corresponding to the increased sound data amplitude, then the haptic amplitude can be ramped down automatically back to a zero level. Again, a pre-programmed mapping between sound features and haptic sensations can be consulted.

The FFT outputs of the embodiment of Fig. 5 tend to be more efficient and provide more information than the filter outputs of the embodiment of Fig. 4. For example, FFT's can provide more detailed frequency information about where a spike in amplitude occurs, the phase offset of waves or features in the sound signal, etc. It should also be noted that the assigning or triggering of different types of haptic sensations described above for Fig. 5 can also be performed in the embodiment of Fig. 4, and the magnitudes of haptic sensations proportional to sound amplitudes of Fig. 4 can be performed in the embodiment of Fig. 5.

In some applications, the ambient background sounds, such as background music in game applications, can be ignored so that only sound effects in the game trigger haptic sensations to be output. Often, the sound effect magnitudes are much higher than the background music amplitudes, allowing the sound effects to be found as spikes above an average amplitude. In other circumstances, background music can ignored and sound effects processed by the type of audio data. For example, if the background music is in a MIDI format and the sound effects are .wav files, then MIDI data can be ignored and wav data processed by the present invention to provide haptic sensations.

Some embodiments can also allow the user to enter preferences which can adjust how the sound data is analyzed, how the haptic effects are assigned, and how the haptic sensations are output. For example, haptic effect strength, the minimum threshold level of amplitude to recognize a sound feature (e.g., so that background music can be better ignored in a game), etc.

The present invention can also be used in other types of application programs besides games. For example, a user's experience of streaming audio can be enhanced by adding haptic sensations to the audio output, so that if the user is contacting the haptic device while listening to the audio output, features in the audio such as music beats, sustained notes, features of speech etc. can be haptically

experienced by the user. Likewise, the present invention can be used with a sound track that is output with streaming video, e.g. over a network such as the Internet.

While this invention has been described in terms of several preferred embodiments, it is contemplated that alterations, permutations and equivalents thereof will become apparent to those skilled in the art upon a reading of the specification and study of the drawings. For example, many different embodiments of haptic feedback devices can be used to output the haptic sensations described herein, including joysticks, steering wheels, gamepads, and remote controls. Furthermore, certain terminology has been used for the purposes of descriptive clarity, and not to limit the present invention.